

DIRECT PLUG-IN TRANSFORMERS



INPUT:100 VAC,50/60Hz
 OUTPUT:3VDC~24VDC,300mA~2.1A,MAX 15VA
 MODEL:AD-XXYYYJ

The "XX" may be 03-24 to indicate different output voltage."03" means 3Vdc; "24"means 24Vdc.
 The "YYY" may be 30~2A1 to indicate different output current. "30 "means 300mA;2A1 means 2.1A
 The "J" means JAPAN plug.

Example:AD-151AJ Means INPUT:100 VAC 50/60Hz, OUTPUT:15VDC, 1.0Amp PSE PIN.

EI 48 AC to DC		CASE
3.0VDC	1.15A-2.1A	48-A1/A2/A3
4.5VDC	1.25A-2.1A	48-A1/A2/A3
5.0VDC	0.95A-2.1A	48-A1/A2/A3
6.0VDC	0.95A-2.1A	48-A1/A2/A3
7.5VDC	0.85A-2.0A	48-A1/A2/A3
8.0VDC	0.8A-1.9A	48-A1/A2/A3
9.0VDC	0.75A-1.6A	48-A1/A2/A3
10.0VDC	0.75A-1.5A	48-A1/A2/A3
11.0VDC	0.6A-1.3A	48-A1/A2/A3
12.0VDC	0.5A-1.2A	48-A1/A2/A3
13.5VDC	0.5A-1.1A	48-A1/A2/A3
14.0VDC	0.5A-1.1A	48-A1/A2/A3
15.0VDC	0.4A-1.0A	48-A1/A2/A3
16.0VDC	0.4A-0.9A	48-A1/A2/A3
17.0VDC	0.4A-0.8A	48-A1/A2/A3
18.0VDC	0.4A-0.8A	48-A1/A2/A3
19.0VDC	0.3A-0.8A	48-A1/A2/A3
20.0VDC	0.3A-0.75A	48-A1/A2/A3
22.0VDC	0.3A-0.6A	48-A1/A2/A3
24.0VDC	0.3A-0.6A	48-A1/A2/A3

With suffix No."DT" for desktop

