

DIRECT PLUG-IN TRANSFORMERS



INPUT:100 VAC,50/60Hz

OUTPUT:7VAC~24VAC,500mA~2.5A,MIN10VA MAX 20VA

MODEL:AA-XXYYYJ

The "XX" may be 07-24 to indicate different output voltage."07" means 7Vac; "24"means 24Vac.

The "YYY" may be 50~2A5 to indicate different output current. "50 "means 500mA;2A5 means 2.5A

The "J" means Japan Plug.

Example:AA-121AJ Means INPUT:100 VAC50/60Hz, OUTPUT:12VAC, 1.0Amp PSE PIN

EI 48 AC to AC		CASE
7.5VAC	1.4A-2.5A	48-A1
8.0VAC	1.2A-2.5A	48-A1
9.0VAC	1.2A-2.2A	48-A1
10.0VAC	1A-2A	48-A1
11.0VAC	0.9A-1.8A	48-A1
12.0VAC	0.9A-1.6A	48-A1
13.5VAC	0.8A-1.4A	48-A1
14.0VAC	0.7A-1.4A	48-A1
15.0VAC	0.7A-1.3A	48-A1
16.0VAC	0.7A-1.2A	48-A1
17.0VAC	0.6A-1.1A	48-A1
18.0VAC	0.6A-1.1A	48-A1
19.0VAC	0.6A-1.0A	48-A1
20.0VAC	0.6A-1.0A	48-A1
22.0VAC	0.5A-0.9A	48-A1
24.0VAC	0.5A-0.8A	48-A1



48-A1

