

DIRECT PLUG-IN TRANSFORMERS



INPUT:100VAC,50/60Hz

OUTPUT:3VDC~24VDC.50mA~600mA,MAX3.6 VA

MODEL:AD-XXYYJ

The "XX" may be 03-24 to indicate different output voltage."03" means 3Vdc; "24"means 24Vdc.

The "YY" may be 05~60 to indicate different output current."05" means 50mA; "60 "means 600mA.

The "J" means JAPAN plug.

Example:AD-0920J Means INPUT:100 VAC 50/60Hz, OUTPUT: 9VDC 200mA PSE PIN.

EI 35 AC to DC		CASE
3.0VDC	600mA MAX	35-A1
4.5VDC	600mA MAX	35-A1
5.0VDC	600mA MAX	35-A1
6.0VDC	500mA MAX	35-A1
7.5VDC	450mA MAX	35-A1
8.0VDC	450mA MAX	35-A1
9.0VDC	400mA MAX	35-A1
10.0VDC	300mA MAX	35-A1
11.0VDC	500mA MAX	35-A1
12.0VDC	300mA MAX	35-A1
13.5VDC	250mA MAX	35-A1
14.0VDC	250mA MAX	35-A1
15.0VDC	200mA MAX	35-A1
16.0VDC	200mA MAX	35-A1
17.0VDC	200mA MAX	35-A1
18.0VDC	200mA MAX	35-A1
19.0VDC	150mA MAX	35-A1
20.0VDC	150mA MAX	35-A1
22.0VDC	150mA MAX	35-A1
24.0VDC	150mA MAX	35-A1



35-A1

